

Features

e-lock-1200LD electromagnetic locks, built-in Door Status Sensor, offer cost effective solution with easy installation & suitable for variety of application. It has no moving part thus keeping maintenance to a minimum


Specification

- 1200lbs holding force
- Dual voltage 12 & 24 Vdc
- Current drawn 500mA / 250mA
- MOV surge protection
- Fail-Safe type
- Unmonitored Model (e-lock-1200)
& Monitored Model (e-lock-1200L)
- Push-off button on armature for instant release
- Dimension : -
Magnet : 265(L) X 66(W) X 40(D) mm
Armature Plate : 185(L) X 60(W) X 17(D) mm



e-lock-1200LD

Door Status Sensor



Wire Terminals

White	COM
Brown	NO
Yellow	NC

Door status Signal

Terminals	Door Closed	Door Opened
White - Brown	Open	Close
White - Yellow	Close	Open


e-lock[®]
Your Security is Our Responsibility

Kyodensha Technologies (M) Sdn Bhd (2057536-M)
Information Communication Technologies (M) Sdn Bhd (640944-K-M)
Digit Innovation Technologies (M) Sdn Bhd (646972-U)

No, 7 Jalan TPP 1/15, Taman Industri Puchong
Batu 12, Jalan Puchong, 47100 Puchong
Selangor, Malaysia

TEL +603 8061 4589 +603 8061 3201
FAX +603 8944 1715
WEB www.elock2u.com
EMAIL sales@elock2u.com


User Guide



Optional Brackets


EL-BKL (L Bracket)

- Adjustable "L" bracket for outward door when the header is narrow.
- Available for e-lock-300, 600 & 1200 Series



EL-BKZ (ZL Bracket)


- Adjustable "ZL" bracket for inward door application.
- Available for e-lock-300, 600 & 1200 Series



Mounting Diagram


Standard Mounting:

- With Filler Plate attached on top of EM Lock.



L Bracket Mounting :

- Mounting with "Adjustable L Bracket" when Door frame is narrow.
- Mounting Procedure :-
Remove the original "Filler Plate" attached to EM Lock, replaced with " Adjustable L Bracket " set.



ZL Bracket mounting :

- Mounting with " ZL Bracket " for In-swing door application.
- Mounting Procedure :-
Remove the original "Filler Plate" attached to EM Lock, replaced with " Adjustable ZL Bracket " set.

